

1/PPR

09/744221
J002 Rec'd PCT/PTO 22 JAN 2001

1

METHOD FOR CONNECTING TERMINAL DEVICES TO EXTERNAL MODEMS

The invention is directed in general to a method for connecting terminal devices ^{and} modems and, stated more specifically, to a method for connecting terminal devices to external modems via local networks (LAN).

^(Asymmetric Digital Subscriber Line)
ADSL (or, generally, xDSL) modems will enable significantly faster Internet access ^{the} in future compared to current modems. Similar to current analog modems, there will also be two versions for xDSL modems: external modems in their own housing that are connected via cable to the terminal device (client) as well as internal modems that are either permanently installed in the terminal device or are in the form of ^{Plug-in} ~~plugin~~ cards that can also be subsequently installed.

External modems must be connected to the terminal device via corresponding interfaces, whereby what is referred to as the Ethernet is especially well-suited because of the high bandwidth and the low costs. Ethernet thereby has the advantage that a plurality of terminal devices can access one or more modems via a local network. This constellation is especially interesting, for example, in networks in small companies.

However, Ethernet ^{an} as interface between terminal device and modem has the disadvantage that the conversion of the data packets ^(Point to Point Protocol) (PPP packets) that are exchanged via the modem path onto the local network (LAN) is very involved.

For this purpose, ^{the Publication} T. Kwok et al., "An Interoperable End-to-end Broadband Service Architecture over ADSL Systems (Version 3.0)", ADSL Forum Contribution 97215, December 1997, proposes the employment of a future standard protocol (layer 2 tunneling protocol) with whose assistance PPP packets can be transmitted via the local network upon employment of UDP/IP. This solution, however, has a number of disadvantages:

1. The protocol known from the Prior Art is very complex and makes high demands of the modem.
2. The proposed protocol offers many functions that are not used for the application in the sense of the present invention.

3. The protocol requires the prior configuration of the IP addresses of terminal device (client) and modem. This, however, is very involved. What would be desirable, in contrast, is a plug-and-play configuration without prior configuration on the part of the user.

4. A direct control of the modem parameters is not possible.

5. *LD5.24* *24* *Ar* The object of the present invention is therefore to avoid the aforementioned disadvantages of the Prior Art and to offer a technique for connecting terminal devices and modems via local networks that is particularly user friendly.

10 According to the present invention, a method for connecting terminal devices to external modems is provided therefor wherein a plurality of modems can enter into communication with the terminal devices with a local network. A number of steps are implemented between one of the plurality of terminal devices and one of the modems for the connection setup. First, a search request is sent from the corresponding terminal device to all modems that are connected to the local network.
15 Those modems that have free resources respond with a reply to the inquiring terminal device. The terminal device subsequently makes a selection from the modem that sent a reply, and a connection setup ensues proceeding from the terminal device to the selected modem by exchanging control information.

The external modems can, in particular, be ADSL modems.

20 The local network can, in particular, be an Ethernet network.

Information for the connection setup and for setting the external modems can be exchanged between the terminal devices and the external modems via an integrated control channel.

25 The search request can contain further particulars about the required bandwidth and/or the required protocol, whereby only those external modems that can meet all requirements according to the further particulars reply to a search request.

Proceeding from the terminal device, settings of the modem can be implemented via an integrated control channel.

30 For flow control of the transmitted data, the respectively receiving terminal device or modem can output start/stop commands with which the data

transmission of the respectively transmitting terminal device or modem can be started or, respectively, stopped.

After the connection setup, echo data that make it possible for the modem to recognize whether the terminal device is active can be exchanged at periodic intervals.

The connection between the modem and the terminal device can be automatically cleared down after a predetermined time when the modem or the terminal device has received none of the echo data during this predetermined time.

For connection cleardown, cleardown ^{data} can be exchanged between the terminal device and the modem, whereby the resources of the connection are in turn released after the cleardown of the connection.

The present invention is explained in greater detail below on the basis of an exemplary embodiment and with reference to the accompanying Figures. ~~Shown~~ are:

Figure 1 ^{is a block diagram showing} the schematic structure of a system for the employment of the inventive method; and

Figure 2 ^{is a chart showing} the executive sequence of the method for the setup of a connection from a terminal device to a modem via a local network.

Figure 1 shows two ADSL modems ^{and} 3, 4 by way of example that can set up a connection between an ADSL line 5 and a local network, for example an Ethernet LAN 6. The ADSL modems ^{and} 3, 4 can be connected to terminal devices (client) ^{and} 1, 2 with the Ethernet LAN 6.

The method for the setup of a connection between a terminal device ^{or} 1, 2 and a modem ^{or} 3, 4 via the Ethernet interface 6 thereby sequences as follows:

Phase 1: Seeking the modem (modems) (steps S1, S2) ^{and}

The searching terminal device ^{or} 1, 2 sends a search request (modem request) to all ADSL modems ^{and} 3, 4 attached to the Ethernet LAN network 6. A specific address is employed for this purpose (also called "limited broadcast address"

255.255.255.255 in IP networks), this ^{leads to} the packet of the search request is received by all modems ^{and} 3, 4 at the connected Ethernet segment. All

modems ^{and} 3, 4 that support the protocol described here and have free resources over and above this, send a reply (modem reply). The terminal device 1, ^{or} 2 receives all replies and is thus informed about all modems that still have free resources. Subsequently, the terminal device 1, ^{or} 2 can select one of the available modems 3, ^{or} 4.

5 Phase 2: Connection setup (steps ^{S5 and S6} S5, S6 [sic]).

The terminal device now initiates a connection setup with the selected modem. Specific control packets (connect request, connect confirm) are exchanged for this purpose, these ultimately leading to a communication relationship (logical connection) between ^{the} terminal device and ^{the} modem. Each side thereby assigns a
10 number (session ID) that, in conjunction with the IP address, unambiguously identifies the communication relationship. Both numbers are contained in all following packets of the connection.

Phase 3: Control of the modem (steps ^{and} S5, S6)

In general, the terminal device now sends various control commands to the
15 modem (similar to current, analog modems). Among other things, the modem can be informed of the destination telephone number to which a connection is to be set up. Moreover, various modem parameters can be influenced such as, for example, bit rate, compression method, error correction, etc. These control commands are based on the commands for analog modems but can also contain specific expansions for xDSL.

20 Phase 4: Data exchange (steps ^{and} S7, S8)

When all settings have been made, the actual data exchange can begin, i.e. PPP packets can be sent bidirectionally via the connection between ^{the} modem and ^{the} terminal device. So that the reception buffers at both sides do not overflow, a flow control is provided according to the start/stop principle. Each receiver can thus stop
25 the transmitter of the cooperating party by sending a stop command and can restart it in turn with a start command. Moreover, the connection can, if desired, be monitored from both sides by periodic transmission of echo packets. As a result thereof, the

modem can recognize when the terminal device no longer reacts or has been switched off.

Phase 5: Connection cleardown (steps S9, S10)

In this phase, the connection between terminal device and modem is cleared down in controlled fashion. To that end, further control packets (release request, release confirm) are exchanged that ultimately lead to the release of the occupied resources.

Message flow

Figure 2 shows the typical message flow between terminal device and modem, beginning with the search phase (search request) up to and including the end of the connection. The individual messages exchanged between terminal device and modem or, respectively, vice versa are described in brief below.

Modem request (step S1)

This message is sent in order to find all modems connected to an Ethernet segment. The message is sent to all stations and, in addition to containing the layer-3 address of the searching terminal device, potentially contains further information such as user name, the desired bandwidth, the desired protocol, etc. These information can be interpreted by the modems, so that only those modems that can meet all requested demands reply.

20 Modem reply (step S2)

All suitable modems reply with this message and thus inform the terminal device of their own layer-3 address. This message is sent directly to the terminal device (no broadcast).

Connect request (step S3)

25 After the terminal device has selected one of the modems, the connection setup is started proceeding from the terminal device. To this end, the terminal device

sends a connect request message to the selected modem. The parameters contained in the modem request message should be repeated in this message and further parameters should be added, if necessary. The terminal device already assigns a session ID in order to enable an unambiguous allocation of the reply of the modem.

5 Connect reply (step S4)

The modem replies with a connect reply message that also contains its own session ID in addition to the session ID assigned by the terminal device. This message tells the terminal device whether the requested connection was accepted or refused. In case of an acceptance, the connection is in place and each side knows the session ID assigned by the other side, this being contained in all further messages. Given a refusal, the connection is cleared down from both sides.

Control (step S5)

Control commands can now be sent to the modem via the existing connection, similar to the case given analog modems. For example, the terminal device can interrogate various modem parameters such as type, the maximum bit rate, the dial capability, the ATM traffic classes that are supported, etc. The terminal device can also potentially influence some modem parameters and can initiate the setup of a dialed connection. In addition to the telephone number, other parameters that are required for the connection setup can also be indicated (for example, the ATM traffic class and the appertaining parameters such as peak bit rate and the like).

ControlAck (step S6)

Each control command is acknowledged by a separate message that can also contain the reply of the modem.

PayloadPacket (steps S7, S8)

25 This message contains the actual payload data, It can be sent in both directions between ^{the} terminal device and ^{the} modem. Payload data are transmitted

unprotected; the loss of payload data can therefore not be recognized within the protocol described here.

Stop

- 5 This message can be sent in order to avoid the overflow of the proper reception buffer. When a stop message is received, payload data are no longer sent in the opposite direction until a start message is received.

Start

See above.

Echo request

- 10 This message is employed in order to check the availability and functionability of the respective cooperating party during an active connection. When an echo request is not answered with an echo reply message within a specific time span, the connection can be cleared down. For example, this mechanism allows the
15 modem to clear down all active network connections when the terminal device was switched off without clearing the connection down in controlled fashion.

Echo reply

The reception of an echo request message is immediately acknowledged with an echo reply message. As a result thereof, the cooperating party is assured that the connection is still active.

20 Release request (step S9)

This message can be sent from both sides and serves the purpose of clearing down an existing connection. The reception of a release request message is acknowledged with a release confirm message by the cooperating party.

Release confirm

- 25 See release request.

Advantages of the disclosed method

The invention has the following advantages over ^{the} known methods:

- No modem-specific data need be configured in the terminal device. The layer-3 address of the modem is determined by the method, and further modem parameters can also be automatically determined by the terminal device without a need for the user to intervene. A simple installation without specific technical expertise is thus enabled (plug-and-play).
- The method enables the direct control of the modem via an integrated control channel. As a result thereof, modem commands can be communicated like via a serial interface.
- The proposed method is significantly simpler to realize.

Possible expansions

The described method assumes that the terminal device already has a functioning Ethernet interface and an appertaining layer-3 address (for example, IP) address available to it. In order to likewise avoid this configuration event and enable a completely independent auto-configuration, the disclosed method can be combined with further protocols such as BOOTP or DHCP. To this end, the modem functions as a simple BOOTP (DHCP) server from which the terminal device can receive its configuration data. The configuration data (essentially the layer-3 address and a few other parameters such as sub-network mask) must be offered on the modem for this purpose. This can be carrier out by the manufacturer or by the network operator. The driver SW ^(software) of the terminal device should be pre-set such that an automatic configuration ensues via BOOTP (DHCP) as well as with the method described here. Any and all user-side configuration is avoided in this way.

The disclosed method can also be expanded in that the search message (modem request) is transported across routers (similar to a BOOTP/DHCP proxy). As a result thereof, modems that are not directly connected to the local Ethernet segment but can only be reached via routers can also be found in larger networks. To this end, the router must contain a proxy function that forwards the sub-message to all connected Ethernet segments (or, respectively, to all segments that support broadcast).

The following advantages can, in particular, be realized by the present invention:

1. In the introduction of the automatic search event with whose assistance all connected modems can be automatically recognized.
- 5 2. In the introduction of a separate control channel via which the modem can be configured and controlled.
3. In the employment of a simple method for flow control between terminal device and modem.
4. In the combination with BOOTP or DHCP, as a result whereof a complete auto-configuration is enabled.

10

0
1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000

IB.28

28